



**AUTHENTIC
HENDRIX™
'69 PSYCH
SERIES FUZZ
FACE®**

THIS PEDAL COMBINES THE TWO DIFFERENT FLAVORS OF FUZZ FACE DISTORTION TONES THAT JIMI HENDRIX USED THROUGHOUT HIS CAREER—AGGRESSIVE SILICON-BASED CRUNCH AND SMOOTH GERMANIUM-BASED SATURATION—ALL IN A MINI MXR HOUSING EMBLAZONED WITH THE TRIPPY, KALEIDOSCOPIIC DESIGNS OF AWARD-WINNING UK-BASED DESIGN CRÛE ILOVEDUST.

External Controls



- 1 BUFF switch toggles between high/low input impedance
- 2 VOLUME knob sets overall volume of effect
- 3 SI/GE switch toggles between silicon (white LED)/germanium (blue LED) fuzz styles
- 4 FUZZ knob controls intensity of fuzz effect
- 5 FOOTSWITCH toggles effect on/bypass (blue LED indicates on)

Basic Operation

Power

The Authentic Hendrix™ '69 Psych Series Fuzz Face® Distortion is powered by the Dunlop ECB003 9-volt adapter or the DC Brick™, Iso-Brick™, and Mini Iso-Brick™ power supplies. This pedal cannot be powered by a battery.

Directions

- 1 Run a cable from your guitar to JHW1's INPUT jack and another cable from JHW1's OUTPUT jack to your amplifier.
- 2 Start with VOLUME and FUZZ controls at 12 o'clock.
- 3 For aggressive silicon-based crunch, set the SI/GE switch to its OUT position, indicated by the white LED. For smooth germanium-based saturation, set the SI/GE switch to its IN position, indicated by blue LED.
- 4 Turn effect on by depressing the footswitch.
- 5 Rotate VOLUME knob clockwise to increase overall volume or counterclockwise to decrease it.
- 6 Rotate FUZZ knob clockwise to increase the amount of fuzz or counterclockwise to decrease it.
- 7 To prevent oscillation when using a wah pedal and preserve high end tone, this pedal's buffer is set to ON by default, indicated by the associated LED. To disable the buffer, set the BUFF switch to its IN position.

Specifications

SILICON / GERMANIUM FUZZ (BUFF ON)

Input Impedance	800 k Ω
Output Impedance	
Max Volume	16 k Ω
Mid Volume	160 k Ω
Max Output Level	-4 dBV
Max Gain	55 dB
Bypass	True Hardwire

SILICON FUZZ (BUFF OFF)

Input Impedance	10 k Ω
Output Impedance	
Max Volume	<16 k Ω
Mid Volume	66 k Ω
Max Gain	55 dB
Bypass	True Hardwire

GERMANIUM FUZZ (BUFF OFF)

Input Impedance	10 k Ω
Output Impedance	
Max Volume	2 k Ω
Mid Volume	115 k Ω
Max Gain	45 dB
Bypass	True Hardwire

POWER REQUIREMENTS

Current Draw	6.8 mA
Power Requirements	9 volts DC

* All specifications made at 1 kHz