

THE ORIGINAL SINCE 1967

cry baby®

LIVE TO PLAY LIVE®



JIMDUNLOP.COM

92503010462REVA

GCB95 ORIGINAL CRY BABY®

POWER

The Original Cry Baby® can be powered by one 9 volt battery (accessed via the bottom of the pedal), a Dunlop ECB003 AC adapter (ECB003E in Europe) or a Dunlop DCB10 DC Brick power supply.

SETUP INSTRUCTIONS

- Run a shielded instrument cable from your guitar to the GCB95's Instrument jack.
- Run another shielded instrument cable from the GCB95's Amplifier jack into your amplifier input.
- Turn on the amplifier and begin playing.
- To turn the pedal on/off, push the toe of the pedal down until you feel a "click".
- By rocking your foot back and forth on the pedal, you can change the effect that the Original Cry Baby has on the tone of your instrument instantaneously.

SPECIFICATIONS

Impedance

Input	800 k Ω
Output	10 k Ω

Filter Parameter

Low Pass	350 Hz ~ 450 Hz
High Pass	1.5 kHz ~ 2.5 kHz

Maximum Level

Input	-8.0 dBV
Output	+10 dBV

Maximum Gain

Heel Down	+19.5 dB
Toe Down	+19 dB

Signal to Noise Ratio*

Heel Down	98 dBV
Toe Down	89 dBV

Current Draw

900 μ A

*OdBV = 1V_{RMS}, A-weighted

